# **Diesel Inverter Marine Generator**

# SLEEPER HC-MG5i

Thanks to the PMG inverter technology, the Sleeper generator HC-MG5i is possible to be made into the smallest, quietest and most powerful of its kind. It delivers the ideal power quality for all on-board appliances such as air-conditioning system, washing machine, cooking devices, battery charging and other AC powered devices. The sleeper generators are 100% water-cooled and equipped with the highly regarded sound insulation. They are specially designed to be light and compact, up to 30% weight and space savings.



# **Product features**

- •Reliable Sleeper water-cooled diesel engine ensure product reliability
- •High efficient water-cooled permanent magnet alternator technology
- •Extremely compact size and light weight for installation
- •Extremely silent by aluminum composite material cabinet
- Virtually vibration free
- •Outstanding voltage stability and pure sines wave are ideal for sensitive electronics
- •Inverter technology saves fuel about 30% and environmentally friendly
- •Local and remote digital display control panels with highly intelligent multi-function protection
- •Parallel technology enables more power and cost saving



# HC-MG5i

60523050 230 V / 50 Hz 60523060 230 V / 60 Hz 60512050 120 V / 50 Hz 60512060 120 V / 60 Hz

MAIN SPECIFICATIONS	
Nominal voltage(V)	230 / 120
Frequency(Hz)	50 / 60
Number of phases	1
Intermittent power	4kW / 5kVA
Continuous power	3.5kW / 4.4kVA
Noise(dBa/7m)	53
Rpm range	2400 - 3000 adjustable
Cooling system	Heat exchanger
Harmonic distortion	≤3%
Frequency stability	±0.1%
Alternator technology	Water-cooled, Brushless, Permanent Magnet
Generator control	PMG Inverter
Inverter (with DDC local)	PMGi 5
Control Panel	Digital Display Control (DDC local + DDC remote)


# **DIESEL ENGINE SPECIFICATIONS**


SLEEPER SP12 Engine model Engine power output 8kW / 3000rpm Cylinder Displacement(cc) 499 Bore x stroke (mm) 92 x 75 Fuel consumption 250 g/kWh Start battery capacity 12VDC / 120Ah Starter battery charge method/ current Handy charger 12V /7A Lubricant At least CF Oil capacity(L) 1.65


# Cabinet dimensions (LxWxH) 450 x 450 x 558 mm Cabinet weight 80 kg Water inlet hose Ø19mm Exhaust hose Ø40mm Fuel Hose Ø 8mm


Ø19mm

# **Dimensions**









Siphon breaker

STANDARD ACCESSORIES	
1.Remote control panel with 15m cable	2. PMG Inverter
3.Waterlock with 2m exhaust hose	4.Expansion tank with 2m water hose
5.Electric fuel pump	6. Fuel-water separator
7. Syphon breaker	8. Seawater filter
9.Non-return valve	10.Seawater pump
11. Handy charger	12. Clamps and screws
13.User's manual	

# **Generator Control Panel GEC4500**

The GEC4500 series controller provides remote start/stop and advanced control, system monitoring, and system diagnostics for optimum performance and compatibility.

### **General Description:**

•Overall Dimension: 152 x 100 x 84.7mm

•Panel Cutout: 116 x 90mm

•Weight: 320g

•Voltage supply: 8V - 35V

•Operating temperature: -25+70 <sup>o</sup>C

•RS485, CAN bus output with SAEJ1939 protocol

# **Digital Display Information:**

- Voltage (V)
- •Frequency (Hz)
- •Current (A)
- Power (kW)
- •Oil Pressure(bar)
- •Coolant Temperature (°C)
- Battery Voltage (V)
- RPM
- •Fuel level
- Running hours
- History log

#### Alarm:

- High temperature
- Over speed
- Over load
- Over current
- Short circuit
- Low oil pressure
- Over/Under voltage
- •Over/Under frequency
- Emergency stop



**Generator Control Panel** 

#### Warnings

- Over/Under battery voltage
- Maintenance request

# **Installation system**

This diagram showcases a complete view of necessary installation facilities for a single Sleeper generator. We highly recommend our respectful users to exclusively employ the facilities originally offered by us.

